

HPE Aruba Networking CX 6100 Switch Series



Neuerungen

- Vereinfacht den IT-Betrieb mit Layer-2-Switch-Serien der nächsten Generation, die zuverlässige und praktische kabelgebundene Zugangskonnektivität der Einstiegsklasse bieten
- Die CX 6100 Series bietet die passende Größe mit 1U-Modellen mit 12, 24 und 48 Anschlüssen und praktischen integrierten 1/10GbE-Uplinks und bis zu 740 W PoE der Klasse 4
- Es verfügt über ein kompaktes und lüfterloses 12-Port-PoE-Modell für beengte Installationen.
- Der CX 6100 bietet Flexibilität bei der Verwaltung und Vereinfachung von Konfigurationen mit HPE Aruba

Übersicht

Die HPE Aruba Networking CX 6100 Switch-Serie ist eine moderne Familie von Einstiegs-Access-Switches, die sich ideal für Zweigstellen, mittelständische Unternehmen und KMU-Netzwerke eignen. Diese Switch-Familie wurde für zuverlässigen, einfachen und sicheren Zugriff konzipiert und bietet eine komfortable kabelgebundene Zugriffslösung für Unternehmensnetzwerke, die Internet der Dinge (IoT), mobile Anwendungen und Cloud-Anwendungen unterstützen.

Bereiten Sie Ihr Netzwerk mit einem leistungsstarken ASIC und dem programmierbaren HPE Aruba Networking CX Switch-Betriebssystem auf zukünftige Anforderungen vor, um ein konsistenteres und effizienteres Bedienererlebnis zu gewährleisten. Diese Layer-2-Switch-Serie verfügt über praktische, integrierte Hochgeschwindigkeits-Uplinks mit bis zu 740 W IEEE 802.3at Class 4 PoE zur Unterstützung von IoT-Geräten wie Sicherheitskameras und drahtlosen Access Points. Ein kompaktes und lüfterloses 12-Port-Modell ist ideal für den Einsatz in ruhigen Arbeitsbereichen. Dank robuster Quality of Service (QoS), Unterstützung für

Networking Central, HPE Aruba Networking Switch Multi-Edit Software, einer benutzerfreundlichen Web-GUI oder einer branchenüblichen CLI.

statisches Routing und IPv6 vereinfachen diese Switches auch die Anschaffung, da keine Softwarelizenzierung für den Switch erforderlich ist.

- Es bietet Skalierbarkeit durch ein 8-köpfiges virtuelles Switching-Framework (VSF) für bis zu 384 Downlink-Ports.
- Layer-2-Funktionen mit statischem Routing und integrierter Switch-Software, für deren Aktivierung kein Abonnement erforderlich ist.

Funktionen

Layer-2-Zugriffsschalter der Einstiegsklasse

Die HPE Aruba Networking CX 6100 Switch Series bietet Gigabit-Konnektivität mit Hochgeschwindigkeits-Uplinks und optionalem PoE, um zuverlässige und praktische kabelgebundene Konnektivität der Einstiegsklasse für Unternehmensfilialen und KMU-Netzwerke bereitzustellen.

Die Switch-Serie bietet ein einfaches und konsistentes Bedienerlebnis mit dem HPE Aruba Networking CX Switch Operating System (AOS-CX), das auf allen HPE Aruba Networking CX Switching-Plattformen verwendet wird.

Es verfügt über vollständig verwaltete Switches der Enterprise-Klasse, die Layer-2-Funktionen mit Unterstützung für statisches Routing, Zugriffskontrolllisten (ACLs), robuste Dienstgüte (QoS), Verkehrspriorisierung, sFlow® und IPv6 bieten.

Die CX 6100 Series bietet Bereitstellung der richtigen Größe mit einer Auswahl an 1U-Modellen mit 12, 24 und 48 Anschlüssen mit praktischen integrierten 1/10GbE-Uplinks und bis zu 740 W PoE der Klasse 4.

Vereinfacht Ownership, da weder Lizenzierung noch Abonnement für eine Switch-Software erforderlich sind.

KI-fähige Leistung und Energie

Die HPE Aruba Networking CX 6100 Switch-Serie ist mit einem dedizierten ASIC ausgestattet, der eine sehr niedrige Latenz, eine erhöhte Paketpufferung und einen adaptiven Stromverbrauch bietet, die für die Anforderungen von KI, Wi-Fi 7 und dem Internet der Dinge (IoT) erforderlich sind.

Es verfügt über bis zu 740 W IEEE 802.3at Klasse 4 PoE mit bis zu 30 W pro Port und unterstützt neuere Wi-Fi 7- und PoE-Geräte.

Die vier integrierten 1/10GbE-Uplinks mit Leitungsgeschwindigkeit minimieren Engpässe auf der Zugriffsschicht, wo Benutzer und Geräte verbunden werden.

Vereinfachte Konfiguration und Verwaltung

Die HPE Aruba Networking CX 6100 Switch-Serie bietet Flexibilität bei der Verwaltung und Vereinfachung von Konfigurationen mit HPE Aruba Networking Central, HPE Aruba Networking Switch Multi-Edit Software, benutzerfreundlicher Web-GUI oder branchenüblicher CLI.

HPE Aruba Networking NetEdit bietet eine Automatisierung, die schnelle netzwerkweite Änderungen ermöglicht und die Einhaltung von Richtlinien nach Netzwerk-Updates verifiziert.

Die Switch-Serie bietet einheitliches Management für kabelgebundene, drahtlose und WAN-Netzwerke mit HPE Aruba Networking Central.

Reduziert manuelle IT-Betriebsaufgaben bei der Erstbereitstellung oder laufenden Konfigurationsänderungen, um das Hinzufügen, Verschieben und Ändern mit farblosen Anschlüssen mithilfe lokaler Benutzerrollen und lokaler MAC-Authentifizierung (LMA) zu ermöglichen.

Die CX 6100-Serie ist mit REST-APIs für die feingranulare Programmierbarkeit von Netzwerkaufgaben bereit für softwaredefiniertes Networking.

Bietet Stacking mit Virtual Switching Framework (VSF) – Skalierbarkeit und Einfachheit

Unterstützt bis zu acht Switches (oder Elemente) in einem Stack via Ketten- oder Ringtopologie.

Bietet die Flexibilität zum Erstellen von Stacks, die große Entfernungen von Hunderten von Metern über einen Campus bis zu Kilometern zwischen verschiedenen Standorten umspannen.

Bietet die Flexibilität, modulare und festverdrahtete CX 6100 Modelle mit 24 und 48 Ports zu kombinieren.

Hat eine vereinfachte Konfiguration und Verwaltung, da die Switches sich beim Stacking verhalten wie in einem einzigen Chassis.

Technische Daten	HPE Aruba Networking CX 6100 Switch Series
Energieverbrauch	Maximale Leistung (ohne PoE): 49,7 W maximale Leistung (ohne PoE): 890 W je nach Modell
Eingangsspannung	100–127 VAC/200–240 VAC
Anschlüsse	12, 24 oder 48 10/100/1000BASE-T-Ports, 1U-Modelle mit praktischen integrierten 1/10GbE-Uplinks, je nach Modell
Latenz	1 Gbit/s: 2,3 µs, 10 Gbit/s: 2,6 µSec, maximal, je nach Modell
Switching-Leistung	Maximal 176 Gbit/s, je nach Modell
Durchsatz	Bis zu 98,6 Mpps, je nach Modell
Speicher und Prozessor	CPU: Dual-Core Arm® Cortex-A9 bei 1016 MHz Speicher: 4 GB DDR3 Flashspeicher: 16 GB eMMC
Netzteilbezeichnung	Internes (festes) Netzteil
PoE-Merkmale	Bis zu max. 740 W PoE-Leistung der Klasse 4, je nach Modell
Managementfunktionen	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software
Betriebstemperatur	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km
Garantie	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer .

SKU-Vergleich

	HPE Aruba Networking CX 6100 12G Class4 PoE 2G/2SFP+ 139W Switch (JL679A)	HPE Aruba Networking CX 6100 24G 4SFP+ Switch (JL678A)	HPE Aruba Networking CX 6100 24G Class4 PoE 4SFP+ 370W Switch (JL677A)
Unterscheidungsmerkmal	Nicht-PoE	Nicht-PoE	Klasse 4 PoE/PoE+
Energieverbrauch	Max. Power (ohne PoE): 21,9W Max. Power (mit PoE): 170W	Max. Power (ohne PoE): 33W	Max. Power (ohne PoE): 32,7W Max. Power (mit PoE): 455W
Eingangsspannung	100–127 VAC/200–240 VAC	100–127 VAC/200–240 VAC	100–127 VAC/200–240 VAC
Anschlüsse	12 x 10/100/1000BASE-T Anschlüsse 2 x 1G/10G SFP-Ports 2 x 1GbE-Ports Unterstützt PoE-Standards IEEE 802.3af, 802.3at 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port	24 x 10/100/1000BASE-T Ports 4 x 1G/10G SFP-Ports 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port	24 x 10/100/1000BASE-T Ports 4 x 1G/10G SFP-Ports Unterstützt PoE-Standards IEEE 802.3af, 802.3at 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port
Latenz	1 Gbit/s: 2,3 s 10 Gbit/s: 2,6 s	1 Gbit/s: 1,5 s 10 Gbit/s: 1,8 s	1 Gbit/s: 1,5 s 10 Gbit/s: 1,8 s
Switching-Leistung	68 Gbit/s	128 Gbps	128 Gbps
Durchsatz	45,1 Mpps	95,2 Mpps	95,2 Mpps
Speicher und Prozessor	Dual Core ARM Cortex A9 @ 1016 MHz 4 GB DDR3, maximal, je nach Modell 16 GB eMMC	Dual Core ARM Cortex A9 @ 1016 MHz 4 GB DDR3, maximal, je nach Modell 16 GB eMMC	Dual Core ARM Cortex A9 @ 1016 MHz 4 GB DDR3, maximal, je nach Modell 16 GB eMMC
Netzteilbezeichnung	Internes (festes) Netzteil	Internes (festes) Netzteil	Internes (festes) Netzteil
PoE-Merkmale	139 W Klasse 4 PoE/PoE+	Modell ohne PoE	370 W Klasse 4 PoE/PoE+
Managementfunktionen	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software
Betriebstemperatur	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km
Gewicht	2,8 kg	2,6 kg	4,2 kg
Produktabmessungen (metrisch)	4,4 x 25,4 x 25,5 cm	4,4 x 44,2 x 20,1 cm	4,4 x 44,2 x 26,8 cm
Garantie	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.

	HPE Aruba Networking CX 6100 48G 4SFP+ Switch (JL676A)	HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 370W Switch (JL675A)	HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 740W Switch (R9Y04A)
Unterscheidungsmerkmal	Nicht-PoE	Klasse 4 PoE/PoE+	Klasse 4 PoE/PoE+
Energieverbrauch	Max. Leistung: 44,2W	Max. Power (ohne PoE): 45W Max. Power (mit PoE): 480W	Max. Power (ohne PoE): 49,7W Max. Power (mit PoE): 890W
Eingangsspannung	100–127 VAC/200–240 VAC	100–127 VAC/200–240 VAC	100–127 VAC/200–240 VAC
Anschlüsse	48 x 10/100/1000BASE-T Ports 4 x 1G/10G SFP-Ports 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port	48 x 10/100/1000BASE-T Ports 4 x 1G/10G SFP-Ports Unterstützt PoE-Standards IEEE 802.3af, 802.3at 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port	48 x 10/100/1000BASE-T Klasse 4 PoE-Ports Unterstützt PoE-Standards IEEE 802.3af, 802.3at 1 x USB-C-Konsolenanschluss 1 x USB Type-A Host-Port
Latenz	1 Gbit/s: 1,9 s 10 Gbit/s: 1,8 s	1 Gbit/s: 1,9 s 10 Gbit/s: 1,8 s	1 Gbit/s: 1,9 s 10 Gbit/s: 1,8 s
Switching-Leistung	176 Gbps	176 Gbps	176 Gbps
Durchsatz	98,6 Mpps	98,6 Mpps	98,6 Mpps
Speicher und Prozessor	Dual Core ARM Cortex A9 @ 1016 MHz 4 GB DDR3, maximal, je nach Modell 16 GB eMMC	Dual Core ARM Cortex A9 @ 1016 MHz 4 GB DDR3, maximal, je nach Modell 16 GB eMMC	CPU: Dual-Core Arm® Cortex-A9 bei 1016 MHz Speicher: 4 GB DDR3 Flashspeicher: 16 GB eMMC
Netzteilbezeichnung	Internes (festes) Netzteil	Internes (festes) Netzteil	Internes (festes) Netzteil
PoE-Merkmale	Modell ohne PoE	370 W Klasse 4 PoE/PoE+	PoE Klasse 4 (740 W)
Managementfunktionen	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software	Flexibles Management dank Unterstützung für HPE Aruba Networking Central, benutzerfreundliche Web-GUI, CLI und HPE Aruba Networking Switch Multi-Edit Software
Betriebstemperatur	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km	Maximal 0 °C bis 45 °C bis zu 1,5 km Abnahme 1 °C je 305 m von 1,5 km bis 3,0 km
Gewicht	3,4 kg	5,0 kg	
Produktabmessungen (metrisch)	4,4 x 44,2 x 24,7 cm	4,4 x 44,2 x 30,5 cm	
Garantie	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.	Eingeschränkte lebenslange Garantie. Siehe Garantiedauer.

Zugehörige Optionen

Die folgenden Optionen sind für diese Serie verfügbar:

SKU	Beschreibung
HPE Aruba Networking Software	
JL639AAE	HPE Aruba Networking NetEdit Single Node 1yr Subscription E-STU
JL640AAE	HPE Aruba Networking NetEdit Single Node 3yr Subscription E-STU
Kabel/Kabelkits	
R9J32A	HPE Aruba Networking USB-A reversible to USB-C PC-to-Switch 3m Cable
R9J33A	HPE Aruba Networking USB-C to USB-C PC-to-Switch 3m Cable
JL742A	HPE Aruba Networking X511 12-port Cable Guard
Montagekits	
J9583B	HPE Aruba Networking X414 1U Universal 4-post Rack Mount Kit
Switches	
JL258A	HPE Aruba Networking 2930F 8G PoE+ 2SFP+ Switch
JL693A	HPE Aruba Networking 2930F 12G PoE+ 2G/2SFP+ Switch
JL662A	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch
JL664A	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch
JL660A	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch
JL658A	HPE Aruba Networking CX 6300M 24-port SFP+ and 4-port SFP56 Switch
JL661A	HPE Aruba Networking CX 6300M 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch
JL663A	HPE Aruba Networking CX 6300M 48-port 1GbE and 4-port SFP56 Switch
JL659A	HPE Aruba Networking CX 6300M 48-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch
JL762A	HPE Aruba Networking CX 6300M 48p 1GbE 4p SFP56 Power-to-Port 2 Fan Trays 1 PSU Bundle
Transceiver	
J4859D	HPE Aruba Networking 1G SFP LC LX 10km SMF Transceiver
J4858D	HPE Aruba Networking 1G SFP LC SX 500m OM2 MMF Transceiver
J8177E	HPE Aruba Networking 1G SFP RJ45 100m Cat5e Transceiver
S2P31A	HPE Aruba Networking 10G LR SFP+ LC 10km SMF C-Class Transceiver
J9151E	HPE Aruba Networking 10G SFP+ LC LR 10km SMF Transceiver
J9150D	HPE Aruba Networking 10G SFP+ LC SR 300m OM3 MMF Transceiver
J9281D	HPE Aruba Networking 10G SFP+ to SFP+ 1m Direct Attach Copper Cable

J9283D	HPE Aruba Networking 10G SFP+ to SFP+ 3m Direct Attach Copper Cable
S2P30A	HPE Aruba Networking 10G SR SFP+ LC 400m OM4 MMF C-Class Transceiver

Zugehörige Services

Die folgenden Services sind für diese Serie verfügbar:

SKU	Beschreibung
-----	--------------

Technische Services

H83A1E	HPE Aruba Networking 1Y 24x7 Technical Support 6100 48G+ 740W SVC
H83G4E	HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC
HV2L5E	HPE Aruba Networking 1Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1L9E	HPE Aruba Networking 1Y Software+Technical Support 6100 24G CL4 Switch SVC
HV1Y7E	HPE Aruba Networking 1Y Software+Technical Support 6100 24G Switch SVC
HV0M3E	HPE Aruba Networking 1Y Software+Technical Support 6100 48G CL4 Switch SVC
HVOZ1E	HPE Aruba Networking 1Y Software+Technical Support 6100 48G Switch SVC
HV2R7E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1S1E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2D9E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 24G Switch SVC
HVOS5E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1E3E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 48G Switch SVC
H83B4E	HPE Aruba Networking 3Y 24x7 Technical Support 6100 48G+ 740W SVC
H83H9E	HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC
HV2M5E	HPE Aruba Networking 3Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1M9E	HPE Aruba Networking 3Y Software+Technical Support 6100 24G CL4 Switch SVC
HV1Z7E	HPE Aruba Networking 3Y Software+Technical Support 6100 24G Switch SVC
HVON3E	HPE Aruba Networking 3Y Software+Technical Support 6100 48G CL4 Switch SVC
HV1A1E	HPE Aruba Networking 3Y Software+Technical Support 6100 48G Switch SVC
HV2T2E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1T6E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2F4E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 24G Switch SVC
HVOUOE	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1F8E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 48G Switch SVC
H83EOE	HPE Aruba Networking 5Y 24x7 Technical Support 6100 48G+ 740W SVC
H83L9E	HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC

HV2P5E	HPE Aruba Networking 5Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1P9E	HPE Aruba Networking 5Y Software+Technical Support 6100 24G CL4 Switch SVC
HV2B7E	HPE Aruba Networking 5Y Software+Technical Support 6100 24G Switch SVC
HV0Q3E	HPE Aruba Networking 5Y Software+Technical Support 6100 48G CL4 Switch SVC
HV1C1E	HPE Aruba Networking 5Y Software+Technical Support 6100 48G Switch SVC
HV2W2E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1W6E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2J4E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 24G Switch SVC
HV0X0E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1J8E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 48G Switch SVC
HV2L0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 12G CL4 Switch SVC
HV1L4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 24G CL4 Switch SVC
HV1Y2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 24G Switch SVC
HVOL8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G CL4 Switch SVC
HV0Y6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G Switch SVC
H82Z5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G+ 740W SVC
HV2R2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1R6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2D4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 24G Switch SVC
HV0S0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1D8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G Switch SVC
H83F9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2R3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1R7E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC
HV2D5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 24G Switch SVC
HV0S1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1D9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G Switch SVC
H83G0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2L3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1L7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 24G CL4 Switch SVC
HV1Y5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 24G Switch SVC
HV0M1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G CL4 Switch SVC
HV0Y9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G Switch SVC
H82Z9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G+ 740W SVC
HV2L4E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1L8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC

HV1Y6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 24G Switch SVC
HV0M2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HVOZ0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2R5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2N9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2Q2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 24G SVC
HY2L3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2M6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G SVC
H82Z8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83A0E	HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6100 48G+ 740W SVC
HV2L6E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1M0E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 24G CL4 Switch SVC
HV1Y8E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 24G Switch SVC
HV0M4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 48G CL4 Switch SVC
HVOZ2E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 48G Switch SVC
HV2L7E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1M1E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV1Y9E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 24G Switch SVC
HV0M5E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HVOZ3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83A2E	HPE Aruba Networking Foundational Care 1Y CTR 6100 48G+ 740W SVC
H83A3E	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6100 48G+ 740W SVC
H82Z6E	HPE Aruba Networking Foundational Care 1Y NBD 6100 48G+ 740W SVC
H82Z7E	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6100 48G+ 740W SVC
HV2K9E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 12G CL4 Switch SVC
HV1L3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 24G CL4 Switch SVC
HV1Y1E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 24G Switch SVC
HVOL7E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G CL4 Switch SVC
HVOY5E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G Switch SVC
H82Z3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G+ 740W SVC
HY2R4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2N8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 24G SVC
HY2L2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2M5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G SVC
H82Z4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G+ 740W SVC

HV2Q8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1R2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2D0E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 24G Switch SVC
HVOR6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1D4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G Switch SVC
H83F5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2Q9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1R3E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2D1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 24G Switch SVC
HVOR7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1D5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G Switch SVC
H83F6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G+ 740W SVC
HV2L1E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 12G CL4 Switch SVC
HV1L5E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 24G CL4 Switch SVC
HV1Y3E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 24G Switch SVC
HVOL9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 48G CL4 Switch SVC
HVOY7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 48G Switch SVC
HV2L2E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1L6E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV1Y4E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 24G Switch SVC
HVOM0E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HVOY8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 48G Switch SVC
HV2L9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 12G CL4 Switch SVC
HV1M3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 24G CL4 Switch SVC
HV1Z1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 24G Switch SVC
HVOM7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G CL4 Switch SVC
HVOZ5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G Switch SVC
H83A6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G+ 740W SVC
HV2S6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1T0E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2E8E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 24G Switch SVC
HVOT4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1F2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G Switch SVC
H83H3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2S7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1T1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC

HV2E9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 24G Switch SVC
HVOT5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1F3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G Switch SVC
H83H4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2M3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1M7E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 24G CL4 Switch SVC
HV1Z5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 24G Switch SVC
HVON1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G CL4 Switch SVC
HVOZ9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G Switch SVC
H83B2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G+ 740W SVC
HV2M4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1M8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC
HV1Z6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 24G Switch SVC
HVON2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HV1A0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2R8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2P2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2Q5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 24G SVC
HY2L6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2M9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G SVC
H83B1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83B3E	HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6100 48G+ 740W SVC
HV2M6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1N0E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 24G CL4 Switch SVC
HV1Z8E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 24G Switch SVC
HVON4E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 48G CL4 Switch SVC
HV1A2E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 48G Switch SVC
HV2M7E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1N1E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV1Z9E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 24G Switch SVC
HVON5E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HV1A3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83B5E	HPE Aruba Networking Foundational Care 3Y CTR 6100 48G+ 740W SVC
H83B6E	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6100 48G+ 740W SVC
H83A7E	HPE Aruba Networking Foundational Care 3Y NBD 6100 48G+ 740W SVC
H83A8E	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6100 48G+ 740W SVC

HV2L8E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 12G CL4 Switch SVC
HV1M2E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 24G CL4 Switch SVC
HV1Z0E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 24G Switch SVC
HV0M6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G CL4 Switch SVC
HVOZ4E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G Switch SVC
H83A5E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G+ 740W SVC
HY2R6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2P0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 24G SVC
HY2L4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2M7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G SVC
H83A4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G+ 740W SVC
HV2S2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1S6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2E4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 24G Switch SVC
HV0T0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1E8E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G Switch SVC
H83G9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2S3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1S7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2E5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 24G Switch SVC
HV0T1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1E9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G Switch SVC
H83H0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G+ 740W SVC
HV2M0E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 12G CL4 Switch SVC
HV1M4E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 24G CL4 Switch SVC
HV1Z2E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 24G Switch SVC
HV0M8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 48G CL4 Switch SVC
HVOZ6E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 48G Switch SVC
HV2M1E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1M5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV1Z3E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 24G Switch SVC
HV0M9E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HVOZ7E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 48G Switch SVC
HV2N9E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 12G CL4 Switch SVC
HV1P3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 24G CL4 Switch SVC

HV2B1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 24G Switch SVC
HVOP7E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G CL4 Switch SVC
HV1B5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G Switch SVC
H83D2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G+ 740W SVC
HV2V6E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1W0E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2H8E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 24G Switch SVC
HVOW4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1J2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G Switch SVC
H83L3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2V7E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1W1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC
HV2H9E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 24G Switch SVC
HVOW5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1J3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G Switch SVC
H83L4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2P3E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1P7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 24G CL4 Switch SVC
HV2B5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 24G Switch SVC
HVOQ1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G CL4 Switch SVC
HV1B9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G Switch SVC
H83D8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G+ 740W SVC
HV2P4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1P8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC
HV2B6E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 24G Switch SVC
HVOQ2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HV1C0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2S4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2P8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2R1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 24G SVC
HY2M2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2N5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G SVC
H83D7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83D9E	HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6100 48G+ 740W SVC
HV2P6E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1Q0E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 24G CL4 Switch SVC

HV2B8E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 24G Switch SVC
HV0Q4E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 48G CL4 Switch SVC
HV1C2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 48G Switch SVC
HV2P7E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1Q1E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV2B9E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 24G Switch SVC
HV0Q5E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HV1C3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83E1E	HPE Aruba Networking Foundational Care 5Y CTR 6100 48G+ 740W SVC
H83E2E	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6100 48G+ 740W SVC
H83D3E	HPE Aruba Networking Foundational Care 5Y NBD 6100 48G+ 740W SVC
H83D4E	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6100 48G+ 740W SVC
HV2N8E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 12G CL4 Switch SVC
HV1P2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 24G CL4 Switch SVC
HV2B0E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 24G Switch SVC
HV0P6E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G CL4 Switch SVC
HV1B4E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G Switch SVC
H83D1E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G+ 740W SVC
HY2S2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2P6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 24G SVC
HY2M0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2N3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G SVC
H83D0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G+ 740W SVC
HV2V2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1V6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2H4E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 24G Switch SVC
HV0W0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1H8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G Switch SVC
H83K9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2V3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1V7E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2H5E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 24G Switch SVC
HV0W1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1H9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G Switch SVC
H83L0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G+ 740W SVC

HV2P0E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 12G CL4 Switch SVC
HV1P4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 24G CL4 Switch SVC
HV2B2E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 24G Switch SVC
HV0P8E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 48G CL4 Switch SVC
HV1B6E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 48G Switch SVC
HV2P1E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1P5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV2B3E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 24G Switch SVC
HV0P9E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HV1B7E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 48G Switch SVC

HPE Aruba Networking Services

HPE Aruba Networking Services vereinfachen und beschleunigen den Lebenszyklus der Netzwerktechnologie, sodass Ihr Netzwerk mit besserer Vorhersagbarkeit und Kosteneffizienz erweitert werden kann. Wenn Sie Ihr eigenes Netzwerk betreiben und Ihre IT effizienter gestalten müssen oder wenn Sie einen Teil der Last auslagern möchten, bieten wir Ihnen die Services, um Ihre Ziele zu erreichen.

Informationen über das Angebot von HPE Services – Aruba Networking erhalten Sie auf:

hpe.com/edge/services

Support-Services

Unser Support-Portfolio bietet die wesentlichen Support-Elemente sowie proaktive und präventive Funktionen, die Ihnen helfen, die Produktivität Ihres Teams zu verbessern und das Beste aus Ihrem Netzwerk herauszuholen. Unsere Support-Kunden profitieren von einer schnelleren Problemlösung, vereinfachten Abläufen und mehr Effizienz sowie weniger Netzwerkproblemen.

Professional Services

Mit tiefgehendem intellektuellem Kapital und speziell entwickelten Tools bietet unser Team eine Reihe von standardmäßigen und personalisierten Professional Services, mit denen Sie aus der HPE Aruba Networking Technologie einen Mehrwert erhalten.

Die Projekt-basierten Services umfassen:

- Planung, Audit und Bewertung
- Prüfung und Design der Architektur
- Implementierung, Migration und Wissenstransfer

Die jährlichen abonnementbasierten Services umfassen:

- Netzwerkoptimierung
- Intelligent Operations
- Customer Experience Management

Unsere [Education Services](#) geben Ihren Mitarbeitern die Möglichkeit, schnell voll einsatzfähig zu werden.

HPE GreenLake für Networking

Unsere NaaS-Lösung ist Teil der HPE GreenLake-Dienstleistungsfamilie und vereinfacht den Netzwerkbetrieb, beschleunigt die Gerätehandhabung und steigert den Wert Ihrer HPE Aruba Networking-Lösung. Wenn Sie fachkundige Beratung und automatisierungsbasierte Abläufe für Ihr Team benötigen, erkunden Sie bitte unseren NaaS-Ansatz durch [HPE GreenLake for Networking](#).

[Weitere technische Informationen,
verfügbare Modelle und Optionen finden
Sie in den QuickSpecs](#)

HPE.com besuchen

[Jetzt chatten](#)

© Copyright 2026 Hewlett Packard Enterprise Development LP. Die Informationen in diesem Dokument können ohne vorherige Ankündigung geändert werden. Die Garantien für Produkte und Services von Hewlett Packard Enterprise werden ausschließlich in der entsprechenden, zum Produkt oder Service gehörigen Garantieerklärung beschrieben. Die hier enthaltenen Informationen stellen keine zusätzliche Garantie dar. Hewlett Packard Enterprise haftet nicht für hierin enthaltene technische oder redaktionelle Fehler oder Auslassungen.

Teile und Materialien: HPE stellt von HPE unterstützte Ersatzteile und Materialien bereit, die für die vertraglich abgedeckte Hardware erforderlich sind.

Teile und Komponenten, die ihre maximal unterstützte Lebensdauer und/oder die maximale Nutzungsbeschränkung gemäß der Beschreibung im Betriebshandbuch des Herstellers, in den QuickSpecs für das Produkt oder im technischen Produktdatenblatt erreicht haben, werden im Rahmen dieser Service nicht bereitgestellt, repariert oder ausgetauscht.

Arm ist eine registrierte Marke von Arm Limited. sFlow ist eine eingetragene Marke von InMon Corp. Alle weiteren genannten Marken von Dritten sind Eigentum der jeweiligen Unternehmen.

Bild kann vom tatsächlichen Produkt abweichen.

[PSN1013114991DEDE](#), Mai, 2026.

HEWLETT PACKARD ENTERPRISE

hpe.com

