

LogiLink®

Emergency Hand Crank Radio with LED Flashlight

Art. No.: SP0074



The Must-Have Emergency Kit

When trapped in natural disasters such as earthquakes, snowstorms, hurricanes with no electricity; go camping/hiking with no lights at night; or when car broke down on the highway with a dead phone battery. The portable multifunctional Emergency Hand Crank Radio is your best tool, always be prepared.



FM/AM/SW
Radio



Flashlight



Solar
Powered



Crank
Powered



SOS
Alarm



Phone
Charger

Multifunctional

4 Modes: Radio/Flashlight/
SOS/USB device charger.

FM/AM/SW1/SW2 Radio

Tune to all your local radio
stations with a long range
antenna.



2 LED Light Modes

Bright flashlight and
SOS mode.

Portable Size

Lightweighted, easy to carry
and store.

Never Power Off with Multiple Power Sources

Built-in rechargeable battery can be recharged by solar panel, hand
crank, through USB-C port, or power with 3 AAA batteries.



Solar power



Hand crank



USB-C charging



3 AAA batteries



Up-To-Date Weather Report

Hear the latest information in your area and be well-prepared.



Emergency SOS Alarm

Call for help with loud siren and SOS light in any catastrophic situation.



Integrated Power Bank

Keep your USB device/smartphone powered in an emergency.

Specifications:

Frequency Band	FM: 87–108 MHz AM: 520–1710 kHz SW1: 5.8–10.0 MHz SW2: 11.6–18.2 MHz
Battery Capacity	1200 mAh
Power By	3.7 V lithium polymer battery or 3x AAA battery
Input Power	USB-C: 5 V/0.3 A (1.5 W) Solar panel: 5 V/0.035 A (0.175 W) Hand crank generator: 5 V/0.4 A (2 W)
Output Power	USB-A: 5 V/0.4 A (2 W)
LED Indicator	Red LED for Power; Green LED for charging
Controls	Radio On/Off and volume knob, AM/FM/SW1/SW2 switch, radio channel tuning dial, phone charger/radio/LED light/SOS switch
Protections	Over charge and discharge
Audio Jack	TS (single channel)
SNR	50 dB
RMS	1 W
Loudspeaker Diameter	50 mm
Loudspeaker Sensitivity	85 dB/W/m $\pm$ 3 dB
Loudspeaker Impedance	8 Ω
Frequency Response	145 Hz – 20 kHz
Frequency Range	45 Hz – 20 kHz
Standby Power Consumption	0.0005 W
Flashlight Modes	Steady, strobe (SOS mode)
Operating Temperature	10–50°C
Operating Humidity	10–90% RH (no condensation)
Housing Material	ABS
Color	Black
Dimensions	13.8 x 6.8 x 4.91 cm
Weight	229 g
Cable Length	45 cm

Package Contents:

- » 1x Multifunctional Radio
- » 1x USB-A to USB-C Charging Cable
- » 1x User Manual

Package Information:

- » Packing Dimension: 85 x 65 x 145 mm
- » Packing Weight: 0.295 kg
- » Carton Dimension: 327 x 305 x 360 mm
- » Carton Q'ty: 40 pcs
- » Carton Weight: 11.8 kg



*The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.



SP0074



Made in China